



OS image for UC-4400A Series (MIL 3.4.1) Release Notes

Version: v1.3	Build: 25101605
Release Date: Oct 27, 2025	

Applicable Products

UC-4400A Series

Supported Operating Systems

Moxa Industrial Linux 3 (Debian 11)

New Features

- Moxa Connection Manager (MCM) v1.7.14:
 - Supports for configuring DHCP lease time and IP range in Wi-Fi Soft-AP mode.
 - Adds encryption mode options for Wi-Fi Soft-AP (OPEN and WPA2) in addition to WPA1+WPA2.
 - The DHCP server now supports the DNS configuration option.
 - Cellular diagnostic function now supports the UC-4450A and UC-4454A with a 5G modem.

Enhancements

- Moxa Connection Manager (MCM) v1.7.14:
 - Improves SIM card switching time for Telit 4G modules.
 - Adds an option to allow non-MCM managed Ethernet interfaces to be controlled by the networking service.
 - Allows an empty IP gateway value to be set.
 - Adds support to enable the DHCP server on multiple LAN interfaces simultaneously (previously limited to one).
 - Improves invalid Wi-Fi SSID and password detection in the MCM GUI; users are now blocked from saving configurations with invalid characters.
 - Allows the & character in Wi-Fi passwords.

Bugs Fixed

- Moxa Computer Interface Manager (MCIM):
 - An issue where the legacy method for configuring push-button actions (supported in MIL 3.0–3.3) was not available in MIL 3.4.0; support has been restored in MIL 3.4.1.
 - An issue where the legacy method for configuring Digital Input (DI) event scripts (supported in MIL 3.0–3.3) was not supported in MIL 3.4.0; support is now restored in MIL 3.4.1.
- Moxa Connection Manager (MCM) v1.7.14:
 - An issue where configuring the out-of-the-box UC cellular connection with a SIM card that has a PIN lock fails to connect to the Internet until the system was rebooted.
 - Unstable reconnections when connecting to Wi-Fi BSSIDs under the same SSID.
 - An issue where an unresponsive GPSD service caused MCM to stop working during GPS port sync by adding a timeout.
 - An issue where MCM v1.2/v1.3 configuration files became incompatible when upgrading to v1.7.5 (MIL 3.4.0) via v1.4 or v1.5.
The issue does not occur when upgrading directly from v1.2/v1.3 to v1.7.5 or v1.4/v1.5 to v1.7.5.
- Moxa Software Updater (MSU):
 - An issue where using the command `mx-sw-updater upgrade --local` to upgrade the system via the



offline method may still require Internet access for dependency download.

Changes

N/A

Notes

- In MIL 3.4.0 released in September, 2025, it introduced new commands in the Moxa Computer Interface Manager (MCIM) utility to make it easier to customize digital input (DI) and push-button (RESET button) event scripts. However, we discovered that the legacy configuration methods supported in MIL 3.0 to 3.3—such as setting the push-button to restore a snapshot or trigger a user-defined script—were unintentionally not backward compatible in MIL 3.4.0. If you have provisioning scripts that rely on "mx-interface-mgmt dio" or "mx-interface-mgmt button" created under MIL 3.0–3.3, please ensure that you use this image.
- If you prefer to upgrade MIL offline, you can use the offline upgrade package included in the downloaded .zip file and apply it with the mx-sw-updater utility.



Version: v1.2	Build: 25061603
Release Date: Sep 19, 2025	

Applicable Products

UC-4400A Series

Supported Operating Systems

Moxa Industrial Linux 3 (Debian 11)

New Features

- Supports mDNS for device discovery with the default port 5353 enabled.
- Moxa Connection Manager (MCM):
 - Adds the "dyn_conf" option to the "moxa-connect-manager" command to modify the configuration cache.
 - Software Wi-Fi AP support enables remote access to devices.

The software Wi-Fi AP supports up to three clients, operates only on the 2.4 GHz frequency, and is recommended for troubleshooting purposes rather than critical data transmission or essential functions.

- Supports "Multi-WAN", a new interface type to route traffic to the interface from which it originates.
- Adds the "mx-connect-mgmt debug diag" command to UC-445xA models with a 5G module.
- Supports Wi-Fi Enhanced Open™ based on the Opportunistic Wireless Encryption (OWE)

Enhancements

- EN 18031-1 (RED) compliant wireless cybersecurity.
To comply with EN 18031-1 wireless cybersecurity, the standard version of Moxa Industrial Linux (MIL) 3.4 includes the following changes:
 - Adds a PAM login policy
The "pam_tally2" mechanism locks the account for 300 seconds after five failed login attempts.
 - Disables SNMPv1 and SNMPv2.
 - Moxa Guardian (MG): Adds a new mode 4 in moxa-guardian.
- Moxa Computer Interface Manager (MCIM):
 - Adds a snapshot script for the push-button.
 - The auto-mount partition feature provides additional log information to verify the success or failure of the mount operation.
 - Supports new DIO commands: add/delete/list/set hook scripts.
 - Supports new button commands: add/delete/list action scripts.
- Moxa Connection Manager (MCM):
 - Adds RSSI and RSRQ signal values.
 - Supports up to two IP target hosts for the ping mechanism.
 - Supports recovery of the cellular module when it unexpectedly stops responding
- Moxa System Decommission (MSM): Enhances the "moxa-system-manager" decommission workflow to improve resilience against interruptions, such as power failures, ensuring reliable system decommissioning.
- All tools: Adds a "-J" command option to support JSON format output for Moxa tools, including MCIM, MCM, MBM, and MSU.
- The Ethernet DHCP client ID, previously fixed to the client's MAC address, can now be configured/modified.
- The username and password fields are auto-populated when the credentials are available in the APN profile data.
- The log-rotate strategy for standard models has been adjusted to apply daily rotation with 14 logs retained in the rsyslog group.

Bugs Fixed

- Configuring eth0 as a Docker interface causes the MCM tool to fail.
- Moxa Bootloader Manager (MBM): The bootloader log is displayed incorrectly in cases where it wraps (e.g., in a circular buffer).

Changes

- Moxa Computer Interface Manager (MCIM):
 - Deprecates the "user-defined" option for a button. Use the "add_action" command to add an action script for unique names.
 - Deprecates the "DIO reload" command for UC-4400A and UC-8200 Series. The active status is now automatically updated.
- Moxa Connection Manager (MCM):
 - The software Wi-Fi AP and Wi-Fi P2P mode cannot be enabled simultaneously
 - The DHCP server will be enabled by default when the Ethernet interface is configured as a LAN.

Notes

- The standard models of the UC-1200A, UC-2200A, UC-3400A, UC-4400A, and UC-8200 Series can achieve EN 18031-1 (RED) compliant wireless cybersecurity via two methods:
 - Clean OS installation: The default system is preconfigured to comply with EN 18031-1 (RED) compliant wireless cybersecurity requirements.
 - System upgrade: After upgrading to the latest OS version, execute the mx-guardian red set command to ensure EN 18031-1 (RED) compliant wireless cybersecurity.
- The "SNR metric" has been renamed to "SINR for LTE/NR cellular interfaces" in both the CLI and D-Bus interfaces.
- Known Issues:

Using the command "mx-sw-updater upgrade --local" to upgrade the system may fail if the device does not have Internet access.

The root cause is that the default installation strategy of "moxa-software-updater" (aligned with APT package management tool) also includes "Recommends" (not mandatory for the standard releases) packages, which may need Internet access to install.

Workaround: Before performing the upgrade, run the command "echo 'APT::Install-Recommends \"false\";' | sudo tee /etc/apt/apt.conf.d/99no-recommends" to exclude the "Recommends" packages from the installation process. After the upgrade is complete, run the command "sudo rm -f /etc/apt/apt.conf.d/99no-recommends" to remove this temporary setting.



Version: v1.1	Build: 241213_061306
Release Date: Feb 19, 2025	

Applicable Products

UC-4400A Series

Supported Operating Systems

Moxa Industrial Linux 3 (Debian 11)

New Features

N/A

Enhancements

- Includes the latest security patches.
- MCM Tool:
 - Supports IPv6 address on LAN1 when the Type changes from "managed" to "none" in Moxa Connection Manager (MCM).
 - Supports configuring the GPS antenna type (active/passive, default: passive) with MCM.
- Supports a serial port to connect to UPort "-G2" Series devices.
- Supports alias name "mg" for "mx-guardian" command.
- MSM Tool:
 - Supports compression function with Moxa System Manager (MSM) to reduce backup file size.

Bugs Fixed

- LAN1 sometimes fails to obtain IPv4 and IPv6 addresses when Type is set to "none" in Moxa Connection Manager (MCM).
- Cellular data usage is displayed as zero in MCM.

Changes

- The "set to default" option will only reset the configuration file and does not restart MCM.

Notes

- Known Issue: The time format of the bootloader log is incorrect (e.g., 20124-mm-dd).
- For detailed release notes, including a change list for the packages, visit the Moxa Industrial Linux document center at: <https://docs.moxa.online/mil/>.



Version: v1.0	Build: 24072202
Release Date: Oct 18, 2024	

Applicable Products

UC-4400A Series

Supported Operating Systems

Moxa Industrial Linux 3 (Debian 11)

New Features

- First release.

Enhancements

N/A

Bugs Fixed

N/A

Changes

N/A

Notes

N/A