

PWR-100電源モジュールシリーズ

EDS-4000/G4000シリーズ用電源モジュール



機能と特長

- 回転可能な設計で、さまざまな設置に対応
- 幅広い電源入力オプションにより柔軟な展開が可能

認証



製品紹介

PWR-100電源モジュールシリーズは、MoxaのEDS-4000/G4000シリーズスイッチ用に設計されています。この電源モジュールに対応しているスイッチは、12/24/48 VDCまたは110/220 VDC/VACを使用できます。

仕様

Power Parameters

Note	<p>The EDS-4000/G4000 Series device model name and power parameters are determined by the installed PWR-100 power module.</p> <p>PWR-100-LV: -LV/-LV-T models PWR-105-HV-I: -HV/-HV-T models PWR-101-LV-BP-I: -LVA/-LVA-T models (PoE support) PWR-103-LV-VB-I: -LVB/-LVB-T models (PoE support)</p> <p>For example: EDS-G4008-T + PWR-100-LV = EDS-G4008-LV-T EDS-G4008-T + PWR-105-HV-I = EDS-G4008-HVT</p> <p>If you install a different power module, refer to the specifications of the corresponding model. For example, if you replace the power module of the EDS-G4008-LV-T with the PWR-105-HV-I, refer to the specifications of the EDS-G4008-HV-T.</p> <p>Power over Ethernet: Only the EDS-4008-4P-2GT-2GS(-T), EDS-4012-8P-4GS(-T), and EDS-G4012-8P-4QGS(-T) models support PoE. If a PoE-capable PWR-100 Series module (PWR-101-LV-BP-I, PWR-103-LV-VB-I) is installed into an EDS-4000/G4000 Series non-PoE model, PoE functionality will not be available.</p>
Connection	2 removable 4-contact terminal block(s)
Input Voltage	PWR-100-LV: 12/24/48 VDC PWR-105-HV-I: 110/220 VDC/VAC PWR-101-LV-BP-I: 48 VDC PWR-103-LV-VB-I: 12/24/48 VDC
Operating Voltage	PWR-100-LV: 9.6 to 60 VDC PWR-105-HV-I: 88 to 300 VDC, 85 to 264 VAC PWR-101-LV-BP-I: 44 to 57 VDC (> 52 VDC for PoE+ output recommended) PWR-103-LV-VB-I: 12 to 57 VDC (> 52 VDC for PoE+ output recommended)

Input Current	PWR-100-LV: 12 to 48 VDC, 1.50 to 0.40 A or 24 VDC, 0.70 A PWR-105-HV-I: 110 to 220 VAC, 50 to 60 Hz, 0.30 to 0.20 A or 110 to 220 VDC, 0.30 to 0.20 A PWR-101-LV-BP-I: 48 VDC, 5.42 A PWR-103-LV-VB-I: 12/48 VDC, 7.46/4.27 A or 24 VDC, 7.26 A
No. of Power Inputs	PWR-100-LV: Redundant dual inputs PWR-105-HV-I: Single input PWR-101-LV-BP-I: Redundant dual inputs PWR-103-LV-VB-I: Redundant dual inputs
Inrush Current (Max.)	-LV models: Max. 0.8 A @ 48 VDC (0.1 to 1 ms)
Overload Current Protection	Supported
Reverse Polarity Protection	Supported

Physical Characteristics

Dimensions	PWR-100-LV: 103 x 98 x 26.6 mm (4.06 x 3.86 x 1.02 in) PWR-105-HV-I: 103 x 98 x 39.9 mm (4.06 x 3.86 x 1.57 in) PWR-101-LV-BP-I: 103 x 98 x 39.9 mm (4.06 x 3.86 x 1.57 in) PWR-103-LV-VB-I: 103 x 98 x 39.9 mm (4.06 x 3.86 x 1.57 in)
Weight	PWR-100-LV: 142 g (0.31 lb) PWR-105-HV-I: 215 g (0.47 lb) PWR-101-LV-BP-I: 176 g (0.39 lb) PWR-103-LV-VB-I: 244 g (0.54 lb)

Environmental Limits

Operating Temperature	The operating temperature is dependent on the EDS-4000/G4000 switch the module is installed in. Please refer to the respective EDS-4000/G4000 Series datasheet for more information.
Storage Temperature	-40 to 85°C (-40 to 185°F)
Ambient Relative Humidity	5 to 95% (non-condensing)

Standards and Certifications

Safety	EN 62368-1 (LVD)
EMI	FCC Part 15 Subpart B Class A
EMC	EN 55032/35 EN 61000-6-2/-6-4
EMS	EN 61000-4-2 (ESD) Level 4 EN 61000-4-3 (RS) Level 3 EN 61000-4-4 (EFT) Level 4 EN 61000-4-5 (Surge) Level 4 EN 61000-4-6 (CS) Level 3 EN 61000-4-8 Level 4
Vibration	ISTA 1A

Warranty

Warranty Period	5 years
-----------------	---------

注文情報

Model Name	Input Voltage	Operating Voltage	Supported Series
PWR-100-LV	12/24/48 VDC	9.6 to 60 VDC	EDS-4008 Series EDS-4009 Series EDS-4012 Series EDS-4014 Series EDS-G4008 Series EDS-G4012 Series EDS-G4014 Series
PWR-101-LV-BP-I	48 VDC for PoE systems	44 to 57 VDC (> 52 VDC for PoE+ output recommended)	EDS-4008 Series EDS-4012 Series EDS-G4012 Series
PWR-103-LV-VB-I	12/24/48 VDC for PoE systems	12 to 57 VDC (> 52 VDC for PoE+ output recommended)	EDS-4008 Series EDS-4012 Series EDS-G4012 Series
PWR-105-HV-I	110/220 VDC/VAC	88 to 300 VDC, 85 to 264 VAC	EDS-4008 Series EDS-4009 Series EDS-4012 Series EDS-4014 Series EDS-G4008 Series EDS-G4012 Series EDS-G4014 Series

© Moxa Inc. All rights reserved.2023年9月1日更新。

Moxa Inc.の明白な許可を written で取得しない限り、本書およびその一部の複製や使用はいかなる方法やいかなる場合でも許可されません。製品の仕様は予告なく変更されることがあります。最新の製品情報については当社のWebサイトをご覧ください。