

ABC-01 系列

適用於網管型交換器和 WLAN 產品的 RS-232 架構配置備份與還原工具



特色與優點

- 堅固耐用的可靠設計
- RS-232 RJ45 主控台連接埠
- 系統重新啟動後自動載入系統配置
- 支援 Moxa 的網管型乙太網路交換器和無線 AP/橋接器/用戶端產品
- 即插即用的系統配置備份與還原

認證



簡介

ABC-01 系列自動備份設定裝置專為系統備份與還原所設計，可提升維護效率並減少系統停機時間。ABC-01 系列可透過 RS-232 主控台連接埠儲存並載入 Moxa 乙太網路交換器及 AWK 無線 AP/橋接器/用戶端的配置。ABC-01 系列可讓您更輕鬆地管理系統參數備份並執行配置。

規格

Interface

Connector	RJ45
-----------	------

Basic Operation

Storage Capacity	128 KB Flash
------------------	--------------

Power Parameters

Input Voltage	3 to 5 VDC (through the RS-232 port's RTS signal)
---------------	---

Physical Characteristics

Housing	PVC molding
IP Rating	IP40
Dimensions	32.5 x 97 x 12 mm (1.28 x 3.82 x 0.47 in)
Weight	50 g (0.11 lb)
Installation	M4 screws (<4 mm)
Cable Length	35±3 cm (including connector)

Environmental Limits

Operating Temperature	0 to 60°C (32 to 140°F)
Storage Temperature (package included)	-40 to 85°C (-40 to 185°F)
Ambient Relative Humidity	5 to 95% (non-condensing)

Standards and Certifications

EMC	EN 55032 Class A
EMI	CISPR 32, FCC Part 15B Class A
EMS	IEC 61000-4-2 ESD: Contact: 4 kV; Air: 8 kV IEC 61000-4-3 RS: 80 MHz to 1 GHz: 10 V/m IEC 61000-4-4 EFT: Power: 2 kV; Signal: 1 kV IEC 61000-4-5 Surge: Power: 2 kV; Signal: 1 kV IEC 61000-4-6 CS: 10 V IEC 61000-4-8 PFMF

Warranty

Warranty Period	5 years
Details	See www.moxa.com/tw/warranty

Package Contents

Device	1 x ABC-01 Series automatic backup configurator
Documentation	1 x quick installation guide 1 x warranty card

訂購資訊

Model Name	Connector	Storage	Operating Temp.
ABC-01	RS-232 (RJ45)	128 KB	0 to 60°C

© Moxa Inc. 版權所有. 2020 年 5 月 22 日更新。

未經 Moxa Inc. 明確書面許可，不得以任何方式複製或使用本文件及其任何部分。產品規格如有變更，恕不另行通知。請至本公司官網了解最新的產品資訊。