

# 佈線套件

## 接線端子模組轉接器



### 特色與優點


- RJ45 轉 DB9 轉接器
- 容易佈線的螺絲式端子

### 簡介

配備螺絲式端子的佈線套件專為在工業環境中使用而設計。尤其是 RJ45 轉 DB9 轉接器型號可以輕鬆地將 DB9 連接器轉換為 RJ45 連接器。

### 接腳安排

#### Mini DB9F-to-TB



DB9-F	TB
1	2
2	1
3	3
4	4
5	5

#### ADP-RJ458P-DB9M



DB9-M	RJ45
1	6
2	5
3	4
4	8
5	3
6	1
7	2
8	7

#### ADP-RJ458P-DB9F



DB9-F	RJ45
1	6
2	4
3	5
4	1
5	3
6	8
7	7
8	2

#### A-ADP-RJ458P-DB9F-ABC01



DB9	RJ45
1	6
2	5
3	4
4	8
5	3
6	1
7	2
8	7

## 規格

### Physical Characteristics

Description	TB-M9: DB9 (male) DIN-rail wiring terminal ADP-RJ458P-DB9M: RJ45 to DB9 (male) adapter Mini DB9F-to-TB: DB9 (female) to terminal block adapter TB-F9: DB9 (female) DIN-rail wiring terminal A-ADP-RJ458P-DB9F-ABC01: RJ45 to DB9 (female) adapter TB-M25: DB25 (male) DIN-rail wiring terminal ADP-RJ458P-DB9F: RJ45 to DB9 (female) adapter TB-F25: DB9 (female) DIN-rail wiring terminal
Wiring	Serial cable, 24 to 12 AWG

### Input/Output Interface

Connector	ADP-RJ458P-DB9F: DB9 (female) TB-M25: DB25 (male) A-ADP-RJ458P-DB9F-ABC01: DB9 (female) ADP-RJ458P-DB9M: DB9 (male) TB-F9: DB9 (female) TB-M9: DB9 (male) Mini DB9F-to-TB: DB9 (female) TB-F25: DB25 (female)
-----------	--

### Environmental Limits

Operating Temperature	TB-M9, TB-F9, TB-M25, TB-F25: -40 to 105°C (-40 to 221°F) Mini DB9F-to-TB, A-ADP-RJ458P-DB9-ABC01: 0 to 70°C (32 to 158°F) ADP-RJ458P-DB9M, ADP-RJ458P-DB9F: -15 to 70°C (5 to 158°F)
-----------------------	---

### Package Contents

Device	1 x wiring kit
--------	----------------

## 訂購資訊

Model Name	Description	Connector
TB-M9	DB9 male DIN-rail wiring terminal	DB9 (male)
TB-F9	DB9 female DIN-rail wiring terminal	DB9 (female)
TB-M25	DB25 male DIN-rail wiring terminal	DB25 (male)
TB-F25	DB25 female DIN-rail wiring terminal	DB25 (female)
Mini DB9F-to-TB	DB9 female to terminal block connector	DB9 (female)
ADP-RJ458P-DB9M	RJ45 to DB9 male connector	DB9 (male)
ADP-RJ458P-DB9F	DB9 female to RJ45 connector	DB9 (female)
A-ADP-RJ458P-DB9F-ABC01	DB9 female to RJ45 connector for the ABC-01 Series	DB9 (female)

© Moxa Inc. 版權所有.2019 年 12 月 25 日更新。

未經 Moxa Inc. 明確書面許可，不得以任何方式複製或使用本文件及其任何部分。產品規格如有變更，恕不另行通知。請至本公司官網了解最新的產品資訊。